

Information regarding Release

HiLCOS Software Version 10.32-Rel

Copyright (c) 2002 – 2020 Hirschmann Automation and Control GmbH, Neckartenzlingen (Germany)

Hirschmann Automation and Control GmbH takes no responsibility or warranty for software not developed or manufactured by Hirschmann Automation and Control GmbH, especially with regard to shareware and other third-party software.

Hirschmann Automation and Control GmbH
Stuttgarter Straße 45-51
72654 Neckartenzlingen
Germany

Internet: <http://www.beldensolutions.com>

2020-12-17

Table of Contents

1. Preface.....	3
2. Known Issues	3
3. Overview on new features as of version 10.32.5410-Rel.....	4
4. Detailed list of new features in HiLCOS 10.32.5410-REL	5
5. Comments	7

1. Preface

HiLCOS is the operating system for the Hirschmann OpenBAT, BAT450, BAT450-11ac, BAT867, BAT-WLC and BAT-Controller Virtual product. This document provides an overview of important information regarding HiLCOS software release 10.32-Rel.

Please note that HiLCOS 10.32-Rel does only support the new BAT-Controller Virtual product.

2. Known Issues

The use of RSTP together with AutoWDS can lead to an unstable AutoWDS network. It is recommended to use AutoWDS with RSTP disabled.

In very rare cases when adding a new Access Point (AP) in the AutoWDS network interactions between neighboring AutoWDS APs can occur. This can cause short-term disruptions of wireless links.

If APs are added in an AutoWDS network before enabling Auto-Accept, these APs must be accepted manually after switching Auto-Accept.

In rare cases the configuration rollout to a managed AP might take around 30 seconds longer when there is a configuration exchange in a redundant WLAN-Controller architecture.

Using the WLC redundancy feature access points do not re-distribute automatically to the preferred controller.

Broadcast attacks are invisible to the Wireless IDS in the actual HiLCOS release.

LANconfig can use SSH, TFTP, HTTP and HTTPS protocols to communicate with the devices. However due to changes regarding force password change, SSH cannot be used with devices which still have a default password. As soon as the default password is changed on the device, SSH will start working normally.

3. Overview on new features as of version 10.32.5410-Rel

BAT-Controller Virtual

You decide which role your BAT-Controller Virtual should play: VPN gateway or WLAN controller. This fully virtualizes the functions of a WLAN controller on virtualization platforms such as VMWare ESXi or Microsoft Hyper-V. The number of managed access points depends on the BAT-Controller License category.

TLS 1.3

Support of the new TLS 1.3 protocol increases the security of device access via WEBconfig.

Elliptic Curve Digital Signature Algorithm (ECDSA)

IKEv2 now supports the Elliptic Curve Digital Signature Algorithm (ECDSA) authentication method. Shorter keys combined with high-efficiency encryption provide the same security.

IKEv2 split DNS

Split DNS allows DNS to resolve specific internal domains to a VPN tunnel, with other DNS requests using a public DNS server.

IKEv2 fragmentation

Fragmentation of IKEv2 messages (per RFC 7383) is handled by the VPN router itself, eliminating the need for the transport network to fragment IKE packets.

Enhanced client reservations in the DHCPv6 server

In the DHCPv6 server, client addresses or prefixes can now be assigned either by means of DUID, MAC address, interface ID (as per RFC 3315) or remote ID (as per RFC 4649).

LEPS-U & LEPS-MAC

Keep control of who is in your Wi-Fi. With LEPS-U (LANCOM Enhanced Passphrase Security – User), individual clients or entire groups each receive a unique Wi-Fi password for an SSID. Using LEPS-MAC, you additionally authenticate the clients by their MAC address—ideal for secure corporate networks.

WAN Policy-Based NAT

WAN Policy-Based NAT allows an easy assignment of static WAN IPv4 addresses to desired services. Due to a NAT action in the firewall rules internal addresses are masked behind a WAN address from the Internet access provider. Ideal for scenarios e.g. for the operation of mail servers and web servers with different WAN addresses.

OCSP responder – more power for Smart Certificate

Maximum security with VPN access: Smart Certificate is the easy way to create digital certificates with your Hirschmann device—without any need for an external certificate authority. This feature has now been extended to include the OCSP (Online Certificate Status Protocol) network protocol, which enables clients to automatically and efficiently query the integrated CA for the status of X.509 certificates.

LISP (Locator / ID Separation Protocol) support

The Locator / ID Separation Protocol (LISP) is a new routing architecture. LISP allows the implementation of highly scalable networks with an integrated routing protocol, tunneling, and overlays. Ideal for service providers or enterprise networks.

Public Spot CSV import

Public Spot management is now even easier: Hotspot users are easily imported and exported by text file (CSV).

4. Detailed list of new features in HiLCOS 10.32.5410-Rel

General

- BAT-Controller Virtual: Support for VMware ESXi and Microsoft Hyper-V
- BAT-Controller Virtual: Support for firmware updates via UPX files
- WEBconfig: Requests for the unencrypted site on port 80 are automatically redirected to the secure site (port 443). This behavior is activated automatically after a device reset.
- "Boot-Cause" is available as an environment variable.
- The RADIUS server supports user-defined RADIUS attributes per RADIUS user.
- A search on the CLI is possible via "find" command.
- Administrators from the table "Further administrators" do no longer have read- or write permission within this table.
- The readscript option "-o" suppresses the output of passwords within scripts.
- The new command "ssldefaults" can be executed from the CLI. After answering a confirmation prompt, the SSL/TLS settings in all submenus of the current configuration are reset to default values.
- The DSCP tag for internal services can now be configured.
- Physical Ethernet ports are now enclosed within the Ifx- and If-tables of the SNMP-IF-MIB.
- The timeout for UDP connections in the firewall was increased to 120 seconds.

Routing & VPN

- The configuration logic of the IPv6 WAN interfaces has been changed.
- WAN Policy-Based NAT: WAN Policy-Based NAT allows address translation (masking) of connections based on firewall rules.
- OCSP responder/server for online certificate check
- Support for LISP (Locator/ID Separation Protocol)
- Configurable target port for IKEv2 and switchable encapsulation (UDP, HTTPS)
- Adaption of the IKEv1/IPSec default crypto algorithms to current standards
- Adaption of the TLS default crypto algorithms to current standards
- Adaption of the SCEP default crypto algorithms to current standards
- BGP: Support for LISP route redistribution
- BGP: The administrative routing distance can be configured per policy.
- Redistribution of RIP routes in BGP
- A particular sender address can be configured for DNS forwarding.
- Besides the Rollout wizard another four programmable WEBconfig wizards can be uploaded.
- The form for Dynamic VPN registration is no longer available
- Enhanced support for DHCP option 43 in the DHCPv4 server
- Support for DHCP option 82 in the DHCPv4 server
- A sender address (loopback address) can be configured via the DHCP relay agent.
- The function automatic WAN tag creation has been omitted
- Option for automatic WAN tag generation omitted.
- The switch for configuring the building of the IPSec SAs is no longer available. IPSec SAs are now built combined.

Wi-Fi

- LEPS-U
LEPS-U (LANCOM Enhanced Passphrase Security - User) gives you the opportunity to specify an individual Wi-Fi password for an SSID for individual clients or whole groups.
- Public Spot user accounts / RADIUS user accounts can be imported and exported via CSV files.
- Public Spot with login after statement of agreement: The point of time for the the day account limits reset is now configurable.
- Active Public Spot sessions are terminated when deleting the user via the "Manage user" wizard.



The **Hirschmann™** BAT Operating System

- The former Public Spot user list has been removed and is no longer supported. Existing configurations are converted to RADIUS entries automatically.
- Support for a dynamic negotiation of the PoE power via LLDP instead of class-based
- The configuration item "Transfer only unicasts, suppress broad- and multicast" is now available for BAT-Controller devices.
- The WLC-controlled automatic radio field optimization now considers DFS channels, too.

5. Comments

Backing up the current configuration

Before upgrading your BAT devices to a new HiLCOS version it is essential to backup the configuration data!

Due to extensive features it is not possible to downgrade to a previous firmware without using the backup configuration.

If you want to upgrade devices which are only accessible via router connections or Wi-Fi bridges, please keep in mind to upgrade the remote device first and the local device afterwards.

Please see the HiLCOS reference manual for instructions on how to upgrade the firmware.

We strongly recommend updating productive systems only after internal tests in client environment.

Despite intense internal and external quality assurance procedures possibly not all risks can be eliminated by Hirschmann Automation and Control GmbH .